



CFP2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

IBM Corporation
IBM eServer p5 575 (1900 MHz, 1 CPU)

SPECfp2000 = 2600
SPECfp_base2000 = 2413

SPEC license #: 11 | Tested by: IBM | Test date: Jan-2005 | Hardware Avail: Feb-2005 | Software Avail: Dec-2004

| Benchmark | Reference Time | Base Runtime | Base Ratio | Runtime | Ratio |
|--------------|----------------|--------------|------------|---------|-------|
| 168.wupwise | 1600 | 74.3 | 2154 | 67.5 | 2370 |
| 171.swim | 3100 | 112 | 2770 | 105 | 2964 |
| 172.mgrid | 1800 | 72.2 | 2492 | 70.8 | 2544 |
| 173.applu | 2100 | 103 | 2045 | 103 | 2045 |
| 177.mesa | 1400 | 116 | 1209 | 110 | 1272 |
| 178.galgel | 2900 | 54.0 | 5372 | 37.7 | 7701 |
| 179.art | 2600 | 27.0 | 9628 | 23.1 | 11276 |
| 183.quake | 1300 | 25.7 | 5059 | 25.7 | 5067 |
| 187.facerec | 1900 | 79.7 | 2384 | 72.5 | 2621 |
| 188.amp | 2200 | 160 | 1374 | 150 | 1468 |
| 189.lucas | 2000 | 59.8 | 3346 | 59.8 | 3346 |
| 191.fma3d | 2100 | 136 | 1549 | 130 | 1616 |
| 200.sixtrack | 1100 | 131 | 842 | 125 | 880 |
| 301.apsi | 2600 | 158 | 1650 | 151 | 1719 |

Hardware

CPU: POWER5
 CPU MHz: 1900
 FPU: Integrated
 CPU(s) enabled: 1 core, 1 chip, 1 core/chip (SMT off)
 CPU(s) orderable: 8
 Parallel: no
 Primary Cache: 64KBI+32KBD (on chip)
 Secondary Cache: 1920KB unified (on chip)
 L3 Cache: 36MB unified (off-chip)/DCM, 8 DCM/SUT
 Other Cache: None
 Memory: 32 GB
 Disk Subsystem: 2x36GB SCSI, 15K RPM
 Other Hardware: None

Software

Operating System: AIX 5L V5.3
 Compiler: XL C/C++ Enterprise Edition Version 7.0 for AIX
 XL Fortran Enterprise Edition V9.1 for AIX
 Other Software: ESSL 4.2
 File System: AIX/JFS2
 System State: Multi-user

Notes/Tuning Information

Portability Flags:

-qfixed used in: 168.wupwise, 171.swim, 172.mgrid, 173.applu,
 178.galgel, 200.sixtrack, 301.apsi
 -qsuffix=f=f90 used in: 178.galgel, 187.facerec, 189.lucas, 191.fma3d

Base Optimization Flags:

Fortran: -O5 -blpdata -lmass
 C: -qpdf1/pdf2
 -O5 -blpdata -qalign=natural

Peak Optimization Flags

168.wupwise: fdpr -q -O3
 -O5 -q64 -blpdata -lmass -qalign=struct=natural -qfdpr
 171.swim: fdpr -q -O3
 -O5 -q64 -qarch=pwr3 -qtune=pwr3 -blpdata -lmass -qalign=struct=natural -qfdpr
 F77=xl f90
 172.mgrid: -qpdf1/pdf2



CFP2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

IBM Corporation
IBM eServer p5 575 (1900 MHz, 1 CPU)

SPECfp2000 = 2600
SPECfp_base2000 = 2413

SPEC license #: 11 | Tested by: IBM | Test date: Jan-2005 | Hardware Avail: Feb-2005 | Software Avail: Dec-2004

Notes/Tuning Information (Continued)

```

-05 -q64 -blpdata -lmass
173.applu: fdpr -q -03
-05 -q64 -blpdata -qalign=struct=natural -qfdpr
177.mesa: -qpdf1/pdf2
-03 -qarch=pwr3 -qtune=pwr3 -qipa=level=2
178.galgel: fdpr -q -03
-05 -blpdata -lmass -qessl -lessl -qfdpr
179.art: -05 -lhmu -blpdata -lmass
183.earthquake: -qpdf1/pdf2
-05 -blpdata -lmass -qipa=partition=large -qmaxmem=-1
187.facerec: fdpr -q -03
-05 -blpdata -lmass -qfdpr
188.ammp: -qpdf1/pdf2
-05 -q64 -blpdata -qalign=struct=natural
189.lucas: -05 -blpdata -lmass
191.fma3d: fdpr -q -03
-05 -blpdata -qalign=struct=natural -qfdpr
200.sixtrack: fdpr -q -03
-05 -blpdata -lmass -qfdpr
F77=xlF90
301.apsi: -05 -blpdata -lmass -qessl -lessl -qsave
F77=xlF90

```

APAR IY62267 was applied to AIX 5L V5.3 to achieve Maintenance Level 1.

SMT: Acronym for "Simultaneous Multi-Threading". A processor technology that allows the simultaneous execution of multiple thread contexts within a single processor core. (Enabled by default)

DCM: Acronym for "Dual-Chip Module" (one dual-core processor chip + one L3-cache chip)
For the 575, only one core is active per chip.

SUT: Acronym for "System Under Test"

ESSL: Engineering and Scientific Subroutine Library

C: IBM XL C for AIX invoked as xlc

Fortran 77: IBM XL Fortran for AIX invoked as xlf90 unless explicitly reassigned

Fortran 90: IBM XL Fortran for AIX invoked as xlf

ulimits set to unlimited.

Large page mode and memory affinity were set as follows:

```

vmo -r -o lpgg_regions=512 -o lpgg_size=16777216 -o memory_affinity=1
chuser capabilities=CAP_BYPASS_RAC_VMM,CAP_PROPAGATE $USER
reboot -q
export MEMORY_AFFINITY=MCM

```

One core was deconfigured and SMT disabled at the open-firmware prompt, using the command

```
boot -s cpu=1 -s smt_off
```