



CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

IBM Corporation
IBM eServer p5 575 (1900 MHz, 1 CPU)

SPECint2000 = 1456
SPECint_base2000 = 1385

SPEC license #: 11 | Tested by: IBM | Test date: Jan-2005 | Hardware Avail: Feb-2005 | Software Avail: Dec-2004

Benchmark	Reference Time	Base Runtime	Base Ratio	Runtime	Ratio	
164.gzip	1400	160	875	156	899	
175.vpr	1400	114	1229	114	1230	
176.gcc	1100	69.6	1581	69.6	1581	
181.mcf	1800	76.7	2347	69.8	2580	
186.crafty	1000	85.7	1167	67.5	1482	
197.parser	1800	144	1250	144	1250	
252.eon	1300	81.2	1601	78.6	1655	
253.perlbmk	1800	185	973	169	1064	
254.gap	1100	89.1	1234	89.1	1234	
255.vortex	1900	88.3	2152	82.9	2291	
256.bzip2	1500	113	1323	111	1351	
300.twolf	3000	192	1560	186	1615	

Hardware

CPU: POWER5
 CPU MHz: 1900
 FPU: Integrated
 CPU(s) enabled: 1 core, 1 chip, 1 core/chip (SMT off)
 CPU(s) orderable: 8
 Parallel: no
 Primary Cache: 64KBI+32KBD (on chip)
 Secondary Cache: 1920KB unified (on chip)
 L3 Cache: 36MB unified (off-chip)/DCM, 8 DCM/SUT
 Other Cache: None
 Memory: 32 GB
 Disk Subsystem: 2x36GB SCSI, 15K RPM
 Other Hardware: None

Software

Operating System: AIX 5L V5.3
 Compiler: XL C/C++ Enterprise Edition Version 7.0 for AIX
 File System: AIX/JFS2
 System State: Multi-user

Notes/Tuning Information

Portability Flags:

```
176.gcc: -ma -DHOST_WORDS_BIG_ENDIAN
186.crafty: -DAIX
252.eon: srcalt=fmax_errno
-I.
253.perlbmk: -DSPEC_CPU2000_AIX
254.gap: -DSYS_IS_BSD -DSYS_STRING_H -DSYS_HAS_TIME_PROTO
-DSYS_HAS_MALLOC_PROTO -DSYS_HAS_CALLOC_PROTO
300.twolf: -DHAVE_SIGNED_CHAR
```

Base Optimization Flags:

```
C: -qpdf1/pdf2
-O5 -blpdata -D_ILS_MACROS
C++: -qpdf1/pdf2
-O5 -lhm -qalign=natural
```

Peak Optimization Flags

```
164.gzip: -qpdf1/pdf2
fdpr -q -O3
-O5 -blpdata -qfdpr
```



CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

IBM Corporation
IBM eServer p5 575 (1900 MHz, 1 CPU)

SPECint2000 = 1456
SPECint_base2000 = 1385

SPEC license #: 11 | Tested by: IBM | Test date: Jan-2005 | Hardware Avail: Feb-2005 | Software Avail: Dec-2004

Notes/Tuning Information (Continued)

```

175.vpr:      -qpdf1/pdf2
              -O5 -blpdata -qalign=natural -D_ILS_MACROS
176.gcc:      -qpdf1/pdf2
              -O5 -blpdata -D_ILS_MACROS
181.mcf:      fdpr -q -O3
              -O5 -blpdata -qfdpr
186.crafty:   -qpdf1/pdf2
              fdpr -q -O3
              -O4 -q64 -qfdpr -qarch=pwr3 -qtune=pwr3
197.parser:   -qpdf1/pdf2
              -O5 -blpdata -qalign=natural -D_ILS_MACROS
252.eon:      -qpdf1/pdf2
              -O4 -qarch=auto -qtune=auto -qalign=natural -D_ILS_MACROS
253.perlbnk:  -qpdf1/pdf2
              -O5 -lhmu -qalign=natural -blpdata -D_ILS_MACROS
254.gap:      -qpdf1/pdf2
              -O5 -blpdata -qalign=natural -D_ILS_MACROS
255.vortex:   -qpdf1/pdf2
              -O5 -lhmu -qalign=natural -blpdata -D_ILS_MACROS
256.bzip2:    fdpr -q -O3
              -O5 -blpdata -qfdpr -D_ILS_MACROS
300.twolf:    fdpr -q -O3
              -O5 -blpdata -qfdpr -qalign=natural

```

Approved alternate-source file 252.eon.fmax_errno.src.alt.tar.gz was used with 252.eon for POSIX-compatibility.

APAR IY62267 was applied to AIX 5L V5.3 to achieve Maintenance Level 1.

SMT: Acronym for "Simultaneous Multi-Threading". A processor technology that allows the simultaneous execution of multiple thread contexts within a single processor core. (Enabled by default)

DCM: Acronym for "Dual-Chip Module" (one dual-core processor chip + one L3-cache chip) For the 575, only one core is active per chip.

SUT: Acronym for "System Under Test"

ulimits set to unlimited.

Large page mode and memory affinity were set as follows:

```

vmo -r -o lpgg_regions=1664 -o lpgg_size=16777216 -o memory_affinity=1
chuser capabilities=CAP_BYPASS_RAC_VMM,CAP_PROPAGATE $USER
reboot -q
export MEMORY_AFFINITY=MCM

```

One core was deconfigured and SMT disabled at the open-firmware prompt, using the command

```
boot -s cpu=1 -s smt_off
```