



CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Supermicro

Motherboard X7DBR-8(2.00GHz, Intel Xeon E5335 processor)

SPECint_rate2000 = 163

SPECint_rate_base2000 = 163

SPEC license #01176 | Tested by: Supermicro | Test date: Nov-2006 | Hardware Avail: Nov-2006 | Software Avail: Mar-2006

Benchmark	Base Copies	Base Runtime	Base Ratio	Copies	Runtime	Ratio
164.gzip	8	118	110	8	117	111
175.vpr	8	110	118	8	108	120
176.gcc	8	56.5	181	8	56.5	181
181.mcf	8	130	129	8	130	129
186.crafty	8	54.5	170	8	54.6	170
197.parser	8	127	132	8	127	132
252.eon	8	50.1	241	8	49.9	242
253.perlbnk	8	76.4	219	8	76.4	219
254.gap	8	75.8	135	8	75.8	135
255.vortex	8	63.4	278	8	63.4	278
256.bzip2	8	113	123	8	113	123
300.twolf	8	133	210	8	133	210

Hardware

CPU: Intel Xeon E5335 processor (2.00 GHz,1333MHz bus)
CPU MHz: 2000
FPU: Integrated
CPU(s) enabled: 8 cores, 2 chips, 4 cores/chip
CPU(s) orderable: 1, 2 chips
Parallel: N/A
Primary Cache: 32KBI + 32KBD on chip per core
Secondary Cache: 8MB(I+D) on chip, per chip (4MB shared per 2 cores)
L3 Cache: N/A
Other Cache: N/A
Memory: 8 X 2GB DDR2 ECC CL5 667MHz FBDIMM
Disk Subsystem: 1 X Seagate Barracuda 120GB 7200 RPM
Other Hardware: N/A

Software

Operating System: Windows Server 2003 Enterprise Edition 32-bits w/ SP1
Compiler: Intel C++ Compiler 9.1 for 32-bit applications
Build 20060323Z Package ID: W_CC_P_9.1.020
Microsoft Visual Studio 2005(for libraries)
SmartHeap Library Version 8.0 from <http://www.microquill.com/>
File System: NTFS
System State: Default

Notes/Tuning Information

```
+FDO: PASS1=-Qprof_gen PASS2=-Qprof_use
Base tuning for C programs: -fast +FDO shlw32M.lib
Base tuning for C++ programs: -fast -Qcxx_features +FDO shlw32M.lib
Portability flags:
176.gcc: -Dalloca=_alloca /F10000000
186.crafty: -DNT_i386
252.eon: -DHAS_ERRLIST
253.perlbnk: -DSPEC_CPU2000_NTOS -DPERLDLL /MT
254.gap: -DSYS_HAS_CALLOC_PROTO -DSYS_HAS_MALLOC_PROTO
Peak tuning:
164.gzip: -fast -Qansi_alias -Oa +FDO
175.vpr: -fast -Qansi_alias +FDO
176.gcc: basepeak=yes
181.mcf: basepeak=yes
186.crafty: -fast -Qansi_alias -Oa +FDO
197.parser: -fast -Qansi_alias +FDO
252.eon: -fast +FDO
253.perlbnk: -fast -Qansi_alias +FDO shlw32M.lib
254.gap: basepeak=yes
255.vortex: basepeak=yes
```



CINT2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

Supermicro

Motherboard X7DBR-8(2.00GHz, Intel Xeon E5335 processor)

SPECint_rate2000 = 163

SPECint_rate_base2000 = 163

SPEC license #01176 | Tested by: Supermicro | Test date: Nov-2006 | Hardware Avail: Nov-2006 | Software Avail: Mar-2006

Notes/Tuning Information (Continued)

256.bzip2: -fast -Oa -Qunroll11 +FDO
300.twolf: -fast -O3 +FDO shlw32m.lib

Tested systems can be used with SC816S-R700 case,
To ensure system stability, a 500W (minimum) ATX power supply [4-pin (+12V), 8-pin (+12V) and 24-pin are required]
Product description located as of <http://www.supermicro.com/products/motherboard/Xeon1333/5000P/X7DBR-8.cfm>

The system bus runs at 1333 MHz

shlw32m-80.lib is the V8.0 SmartHeap library renamed to co-exist with older versions